

AC VOLTAGE CONTROLLER/MONITOR

Model : PAV-6068

ISO-9001, CE, IEC1010



Lutron

LUTRON ELECTRONIC

The Art of Measurement

AC Voltage CONTROLLER/MONITOR

Model : PAV-6068

FEATURES

* Professional ACV meter with standard DIN case (96 x 48 mm) and Control/Alarm function.
* Microprocessor circuit ensures high accuracy and provide special functions and features.
* Large red LED display, high brightness and easy to read.
* Input signal (without PT) : ACV : 1.0 to 600.0 ACV, 40 to 400 Hz.
* True rms for ACV measurement.
* Voltage input can cooperate the external PT (Potential transformer) to expand the measurement range. The PT range can be adjusted with default.
* Control setting, Hi/Lo alarm setting.
* Control relay output, alarm relay output.
* Control Relay will make action when the reading value reach to control value.
* Alarm Relay will make action when the reading value reach to high/low alarm value.
* Hysteresis value setting for control and alarm function.
* Power : 90 ACV to 264 ACV, 50/60 Hz.
* RS232/USB computer interface.
* Option data acquisition software.

GENERAL SPECIFICATIONS

Display	Large LED display. 4 digit LED . 14 mm (0.55 inch) digit height . 5 indicators . PV (process value) indicator SV (set value) indicator Control out indicator Alarm out indicator V (ACV) indicator	
Circuit	Custom chip of microprocessor LSI circuit.	
ACV measurement	1.0 ACV to 600.0 ACV * True rms value * Without PT.	
Sampling Time	Approx. 0.8 second.	
Relay Output	Number	2 relays
	Function	Relay 1 : Control relay. Relay 2 : High/Low alarm relay.
	Max load	0.5 ACA/250 ACV 0.5 DCA/24 DCV * Do not apply the relay contact load current > 0.5 A, other wise the relay may be damaged permanently without warranty.
Setting Function	1st layer setting procedures	CtLo (Control low limit) CtHi (Control high limit) ALLo (Alarm low limit) ALHi (Alarm high limit)
	Second layer setting procedures	PtSt (PT rate setting) CtHy (Control hysteresis value setting) ALHy (Alarm hysteresis value setting)

Over input	" - - - - " mark indication.
Zero Adjustment	Automatic adjustment.
Data Output	RS232 / USB PC Computer interface. * Connect the optional RS232 cable , UPCB - 02 will get the RS232 plug. * Connect the optional USB cable, USB - 01 will get the USB plug.
Operating Temperature	0 to 50 °C .
Operating Humidity	Less than 80% R.H.
Power Supply	90 to 260 ACV, 50/60 Hz.
Power Consumption	Approx. 3.3 VA/AC 110V. Approx. 4.9 VA/AC 220V. * Under no load
Weight	261 g/ 0.57 LB.
Dimension	DIN size : 96 x 48 mm. Panel cut size : 92 x 46 mm. Depth : 110 mm.
Accessories Included	Instruction manual..... 1 PC Case holder with screw..... 2 PCs
Optional Accessories	USB cable , USB - 01 RS232 cable , UPCB - 02 Data Acquisition software SW-U801-WIN * Real time SD card datalogger DL-9602SD * GSM controller, GSM-889. * Interface cable (cable between meter to GSM-889), GMCB-89.

ELECTRICAL SPECIFICATIONS

Without PT(direct input)

Range	1 ACV to 600 ACV
Resolution	0.1 ACV
Accuracy	± (0.5 % + 5d) reading
Remark :	* Measuring Signal come from the rear terminals . * T11, T12 max. ACV input : AC 600 V . * Accuracy is test under input signal is sine wave, 50/60 Hz. * ACV frequency response is from 40 to 400 Hz. * ACV measurement is True RMS value. * Accuracy value is specified within 23°C ± 5°C

With PT (Potential transformer)

Range	10 ACV to 9999 ACV
Resolution	1 ACV
Accuracy	± (0.5 % + 5d) reading
Remark :	* Measuring Signal come from the rear terminals . * T11, T12 max. ACV input : AC 600 V . PT (Potential transformer) adjust value : x 1 to x 100. * Accuracy is test under input signal is sine wave, 50/60 Hz. * Accuracy is specified for the meter only, not include the accuracy of PT (Potential transformer) .